


FBA 32L6/U6-Mini Booster Amplifier L6 and U6 Band



Features:

- Operating Across Full L6 band (5.725-6.450GHz) and U6 band (6.40-7.125GHz)
- Proprietary GaN FETs and Advanced Machining Delivering Best in Class Efficiency
- RF Feedback Port For Predistortion Allows Further Improvement in Linearity
- Direct Gate and Drain Control for Envelop Tracking, Allowing Further Efficiency Improvement
- Integrated Temperature Sensor
- Very Small Form Factor, 65mm x 36mm x 15mm
- SMA Connectors For Simplified Radio Insertion

The Range of Point-to-point Backhaul Radio Links, Operating in L6/U6 Bands, Can be Significantly Increased By The Addition of This Ultra Compact GaN Amplifier

Amplifier Specifications

L6 Specifications

At Operating Power of 37dBm:

 Gain
 10.5dB

 IM3
 -50dBc

 IM5
 -50dBc

PAE 25% (without envelop tracking)

Saturated Output Power 24dBm, 32W

EMEA Americas

Filtronic plc

NETPark

Sedgefield

TS21 3FD

United Kingdom

Filtronic Wireless Inc.

700 Marvel Rd

Salisbury

MD 21801

United States of America

+44 1740625163 +1 410 202 8811

All rights reserved

Specifications are subject to change



FBA 32L6/U6